

HAI Omni family of Home Control Systems	Omni LT	Omni Ile	OmniPro II
HAI Lighting/Rooms	2	8	31
Lighting Scenes	16	64	128
Lighting Addresses	16	64	250
Zones	8	16	16
Zone Expansion Total	24	48	176
2 wire smoke loops	1	4	4
4 wire smokes	24	48	176
Thermostats	2	4	64
Consoles / Keypads ***	4	8	16
OmniTouch 5.7 Touchscreens	3 *	7 **	15 **
12 volt triggers (with expansion)	2 (10)	8 (8)	8 (136)
Serial ports (with expansion)	1 (2)	5 (6)	5 (6)
Ethernet port	No	Yes	Yes
Audio Control	Yes	Yes	Yes
Flash Memory	No	Yes	Yes
User Codes	8	16	99
Programming Lines	100	500	1,500
Vocabulary	195	550	550
Custom Vocabulary	No	No	Yes
Depluggable Terminal Strips	No	Yes	Yes
Format	Contact ID 4/2 3/1	Contact ID 4/2 3/1	Contact ID 4/2 3/1
Transformer Required	16.5V 40VA	24V 40VA	24V 40VA
Battery (Typical)	12V 7 Ah	12V 7 Ah	12V 7 Ah
Aux current Max	500 mA	1:00 AM	1:00 AM
Bell current max	1:00 AM	1:00 AM	1:00 AM
Aux current (UL 24 hr)	200 mA	250 mA	250 mA
Bell current (UL 24 hr)	350 mA	300 mA	300 mA
Number of 16 Zone Hardwire Expanders (10A06-1) Supported	0	2	2
Number of Expansion Boards (17A00-x) Supported	0	0	8
Number of Expansion Boards (22A00-1) Supported	1	0	0
Warranty	2 years	2 years	3 years

* Recommend using a Touchscreen Hub & Power Supply (HAI Part # 32A30-x) for 2 or more OmniTouch 5.7 Touchscreens.

** Recommend using a Touchscreen Hub & Power Supply (HAI Part # 32A30-x) for 3 or more OmniTouch 5.7 Touchscreens.

*** Systems must include at least one console. Each OmniTouch 5.7 Touchscreen uses 1 console address.