



Remote Controlled Light Dimmers



EZE-SW-101




EZE-SW-102



EZE-SW-103



CL-RUD-101



CL-RUD-102

PRODUCT FEATURES

- Compatible to all ClickOn remote controls
- Fits standard 2 x 4 wall boxes
- No additional wiring required when replacing existing light switches
- Can be operated without a remote control
- User friendly programming
- Easy operation: Press and release button to switch light ON/OFF. Press and hold button to dim light.
- Built in radio receiver and power failure memory
- Multi-way switching can be implemented when used with one or more ClickOn wall-mount remote controls

DIMMERS FOR 220V INCANDESCENT AND HALOGEN LAMPS

Part Number:

- * 1-Lever: EZE-SW-101
- * 2-Lever: EZE-SW-102
- * 3-Lever: EZE-SW-103

- Remote on/off and dimming control.
- Available in 1, 2 and 3-lever configurations.
- Suitable for 220V incandescent and 220V halogen lamps
- NOT suitable for low voltage transformers and ceiling fans.
- Maximum load: 300W per lever.
- Minimum load: 40W per lever.
- Memory capacity: Up to 12 remote control channels.

UNIVERSAL DIMMERS FOR 220V AND LOW VOLTAGE LIGHTING

Part Number:

- * 1-Lever: CL-RUD-101
- * 2-Lever: CL-RUD-102

- Remote on/off and dimming control.
- Suitable for:
 - * Incandescent lamps.
 - * High voltage (220V) halogen lamps.
 - * Low voltage halogen lamps with electronic transformers
- Available in 1 and 2 lever configurations
- Led indicator: 1 flash for ON, 2 flashes for OFF
- Maximum load for CL-RUD-101: 400W
- Maximum load for CL-RUD-102: 250W per lever
- Memory capacity: Up to 24 remote control channels
- Overload and short circuit protection
- NOT suitable for ceiling fans and magnetic transformers.