



Multi-user Code Hopping Gate Receiver



Base unit (receiver) with backup module:
CL-MUG-2K



Display Unit: CL-MGD-10

PRODUCT FEATURES

- Code Hopping for secure access control
- Up to 2000 users
- 3 Single contact relay outputs
- Easy programming via separate plug in display/programming unit.
- RS232 interface with Windows software available.
 - * Emulate display unit.
 - * Backup profile to the PC hard disk.
 - * Restore a profile from the PC hard disk.
- Easy to manage individual users.
- Lost or stolen remote controls can be removed and replaced thus preventing access by the old remote control.
- Relay pulse lengths programmable from 1 to 8 seconds
- Removable backup module enables easy replacement of a damaged or stolen unit. No reprogramming of remote controls required.
- Programming without the backup unit is not possible thus preventing unauthorized programming of the unit.
- Range: Up to 100m
- Supply: 12 to 24V AC/DC
- Connections: via screw type terminals
- Dimensions:
 - * Base unit (receiver): 62 x 95 x 24mm
 - * Display unit: 57 x 100 x 24mm
- Part Numbers:
 - * Base Unit (Receiver): CL-MUG-2K (Backup module included)
 - * Display Unit: CL-MGD-10
 - * Replacement backup module: CL-MGM-10
 - * PC Software and RS232 interface cable: CL-MGS-10